

## Remote control panel TX6

Panels TX6 can be used for remote controlling of the matrix switchers and graphics systems *TEXTUS LOGO*, *TEXTUS AIR*. Device TX6, operating as matrix switcher controller, can either be as X (for controlling only one output line) or as XY panel (for controlling all matrix switcher). To control graphic systems, TX6 is used as one line (X) 32 buttons panel, with two function buttons (title, logo on/off). It is possible to use two switching modes – either simply pressing any source key or using *TAKE* button. Video and audio control can be separated and in

that case video and audio matrix switchers are used as layers.

Switches on the rear panel provide selection of



the output line (for X controlling panels). No connection LED indicator is located on the front panel. Control panel interface as option can be RS232 (COM), USB or LAN.

Panels can be manufactured as:

- X (one line) 8+2 buttons
- XY 16+2 buttons
- X (one line) 16+2 buttons
- XY 32+2 buttons

Special customer marks for each key can be inserted under the cap. Front panel buttons are illuminated by back green light.



### Technical specifications:

Interface:	RS232 (COM), USB, LAN
No connection indicator:	LED on the front panel
Power:	~ 220V, 5VA
Dimensions:	483x44x65mm (19", 1U)
Weight:	1.2ka

